

# [ZPL Windows SDK]

[Printer ZPL Command Development Manual v1.4]

1. Information of the Manual.....	4
2. Operation System.....	4
3. Remark.....	4
4. Method.....	5
4.1 PrinterCreator.....	5
4.2 PrinterCreatorS.....	6
4.3 PrinterDestroy.....	7
4.4 PortOpen.....	8
4.5 PortClose.....	10
4.6 WriteData.....	11
4.7 ReadData.....	12
4.8 DirectIO.....	13
4.9 ZPL_StartFormat.....	15
4.10 ZPL_EndFormat.....	16
4.11 ZPL_ScalableFontText.....	17
4.12 ZPL_Text.....	19
4.13 ZPL_BarCode39.....	22
4.14 ZPL_Pdf417.....	24
4.15 ZPL_CodeEan8.....	26
4.16 ZPL_UpceCode.....	28
4.17 ZPL_BarCode93.....	30
4.18 ZPL_BarCode128.....	32
4.19 ZPL_CodeEan13.....	34
4.20 ZPL_MicroPdf417.....	36
4.21 ZPL_QRCode.....	38
4.22 ZPL_UpcExtensions.....	40
4.23 ZPL_UpcaBarcode.....	42
4.24 ZPL_SetChangeFontEncoding.....	44
4.25 ZPL_SetChangeCaret.....	46
4.26 ZPL_SetChangeDelimiter.....	47
4.27 ZPL_SetChangeTilde.....	48
4.28 ZPL_GraphicBox.....	49
4.29 ZPL_GraphicCircle.....	51
4.30 ZPL_GraphicDiagonalLine.....	52
4.31 ZPL_GraphicEllipse.....	54
4.32 ZPL_PrintImage.....	56
4.33 ZPL_GraphicSymbol.....	57
4.34 ZPL_SetDiagnosticsMode.....	59
4.35 ZPL_SetLabelHome.....	60
4.36 ZPL_SetLabelLength.....	61
4.37 ZPL_SetLabelShift.....	62
4.38 ZPL_SetLabelTop.....	63
4.39 ZPL_SetPrintMode.....	64
4.40 ZPL_SetMediaType.....	65
4.41 ZPL_SetPrintingMirrorImage.....	66
4.42 ZPL_SetPrintOrientation.....	67
4.43 ZPL_SetPrintRate.....	68
4.44 ZPL_SetPrintWidth.....	69
4.45 ZPL_SetSerialCommunications.....	70
4.46 ZPL_SetPrintDarkness.....	72
4.47 ZPL_SetTearOffAdjustPosition.....	73
4.48 ZPL_PrintConfigurationLabel.....	74
4.49 ZPL_GetPrinterIpAddress.....	75
4.50 ZPL_GetPrinterStatus.....	76
4.51 ZPL_GetLabelLength.....	78
4.52 ZPL_GetLabelWidth.....	79

4.53 ZPL_GetPrinterSeriesNumber.....	80
4.54 ZPL_GetPrinterMacAddress.....	81
4.55 ZPL_GetPrinterName.....	82
4.56 ZPL_GetPrinterFirmwareVersion.....	83
4.57 ZPL_GetPrinterDpi.....	84
4.58 ZPL_LearnLabel.....	85
4.59 ZPL_SetReprintAfterError.....	86
4.60 ZPL_SetNetworkSetting.....	87
4.61 ZPL_SetMediaTracking.....	89
4.62 ZPL_SetUserFontName.....	90
4.63 ZPL_SetVietMode.....	91
4.64 ZPL_SetVietFontEncoding.....	92
4.65 ZPL_Text_Block.....	93

## **1. Information of the Manual**

This SDK manual provides the dll file information for Windows application development.

We continuously promote and update the function and quality of all our products. Any change to the product specification and the manual will be without any further notice.

## **2. Operation System**

- Windows 2003/XP/7/8/10

## **3. Remark**

- When error code Return Value is greater than 0, it is the internal error of Windows system, please refer to related help file.

## 4. Method

### 4.1 PrinterCreator

Set up the target printer of specified model (should create target printer before using any function).

```
int PrinterCreator(  
  
    void* handle,  
  
    const TCHAR* model  
  
);
```

#### Parameter:

*void\* handle*

[in,out] The created target printer object.

*const TCHAR\* model*

[in] Specify the model of target printer.

#### Return Value:

Error Code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_INVALID_MODEL	-8	Invalid model name

## 4.2 PrinterCreatorS

Set up the target printer of specified model, the function is same to PrinterCreator (should create target printer before using any function).

**void\* PrinterCreatorS(**

**const TCHAR\* *model***

**);**

### **Parameter:**

*const TCHAR\* model*

[in] Specify the model of target printer

### **Return:**

Success : return the handle of printer object.

Fail: return NULL, invalid handle.

## 4.3 PrinterDestroy

Release the resource of specified model printer that has set up (after operation completed and no more operation for printer, it should release the printer that has set up).

**int PrinterDestroy(**

**void\* *handle***

**);**

### Parameter:

*void\* handle*

[in] The handle of target printer object which needs to release.

### Return Value:

Error Code	Value	Description
E_SUCCESS	0	Normal
E_BAD_HANDLE	-6	Invalid handle

## 4.4 PortOpen

Open the communication port and connect with the printer. After successfully connected, other functions can be used. If failed connecting, please check the error information.

```
int PortOpen(  
  
    void* handle,  
  
    const TCHAR* ioSettings  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*const TCHAR\* ioSettings*

[in] Set up the parameter of communication port that connected to the target printer. Please see as below:

### Configuration List:

Type	Configuration	Description	Sample
USB	<b>USB</b> [ <i>Position/Model/PortNum</i> ]	USB: connect any USB printer of our company USB[ <i>Position</i> ]: When connecting to multi printers of our company, can specify connecting to one particular USB printer through USB position information (Position parameter)	USB USB,Port_#0004.Hub_#0003 USB,LPG4 USB,USB001
NET	<b>NET</b> , <i>IP Add (IPV4)</i> [ <i>Port</i> ]	Specify the IP add and port of internet printer. If not specifying port, the default port is 9100.	NET,192.168.0.36 NET,192.168.0.36,9100
COM	<b>COMn</b> ,BAUDRATE_ <i>rate</i>	Specify the number and baud rate of connected serial port .	COM5,BAUDRATE_19200
LPT	<b>LPTn</b>	Specify the number of connected parallel port.	LPT1

Note: [ ] indicates selective parameter

\*If you connect to many different printers of our company at the same time,it is recommended to connect them by "USB,model".



**Return Value:**

Error Code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_OPEN_FAILED	-311	Port open failed

## 4.5 PortClose

This function is to close the communication port and disconnect with the printer.

```
int PortClose(  
  
    void* handle  
  
);
```

### Parameter:

*void\* handle*  
[in,out] The created target printer object.

### Return Value:

Error Code	Value	Description
E_SUCCESS	0	Normal
E_BAD_HANDLE	-6	Invalid handle

## 4.6 WriteData

This function is to send data to the printer.

```
int WriteData(  
  
    void* handle,  
  
    unsigned char* writeData,  
  
    unsigned int writeNum  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*unsigned char\* writeData*

[in] The data sent to the printer (hex string).

*unsigned int writeNum*

[in] The length of the data sent.

### Return Value:

Error Code	Value	Description
E_SUCCESS	0	Normal
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout
E_IO_READ_FAILED	-331	Read failed
E_IO_READ_TIMEOUT	-332	Read timeout

## 4.7 ReadData

This function is to read the printer data.

```
int ReadData(  
  
    void* handle,  
  
    unsigned char* readData,  
  
    unsigned int readNum,  
  
    unsigned int* preadedNum  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*unsigned char\* readData*

[in] Printer data that needs to be read.

*unsigned int readNum*

[in] The length of data that needs to be read.

*unsigned int\* preadedNum*

[in] The length of the data actually read.

### Return Value:

Error Code	Value	Description
E_SUCCESS	0	Normal
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_READ_FAILED	-331	Read failed
E_IO_READ_TIMEOUT	-332	Read timeout

## 4.8 DirectIO

This function is for the user to customize the data sent and read by the printer. If some functions do not provide a function interface, the user can send command data to the printer through this interface.

```
int DirectIO(  
  
    void* handle,  
  
    unsigned char* writedata,  
  
    unsigned int writeNum,  
  
    unsigned char* readdata,  
  
    unsigned int readNum,  
  
    unsigned int* preadedNum  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*unsigned char\* writedata*

[in] The data written to the printer.

*unsigned int writeNum*

[in] The length of the data written to the printer.

When writeNum=0, the write data operation is not performed.

*unsigned char\* readdata*

[in,out] Get the data returned by the printer.

*unsigned int readNum*

[in] Preset the length of data that needs to be read.

When readNum=0, the read data operation is not performed.

*unsigned int\* preadedNum*

[in,out] The length of the data actually read.

**Return Value:**

Error Code	Value	Description
E_SUCCESS	0	Normal
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout
E_IO_READ_FAILED	-331	Read failed
E_IO_READ_TIMEOUT	-332	Read timeout

## 4.9 ZPL\_StartFormat

This function is to indicate the beginning of a new label format.

```
int ZPL_StartFormat(  
  
    void* handle  
  
);
```

### Parameter:

*void\* handle*  
[in,out] The created target printer object.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.10 ZPL\_EndFormat

This function is to indicate the end of a label format.

```
int ZPL_EndFormat(  
  
    void* handle  
  
);
```

### Parameter:

*void\* handle*  
[in,out] The created target printer object.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout



## 4.11 ZPL\_ScalableFontText

This function is to print scalable fonts.

```
int ZPL_ScalableFontText(  
  
    void* handle,  
  
    int xPos,  
  
    int yPos,  
  
    char fontName,  
  
    int orientation,  
  
    int fontWidth,  
  
    int fontHeight,  
  
    char* text  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*char fontName*

[in] Font(range: A-Z and 0-9).

*int orientation*

[in] Print direction.

0 : normal

90 : Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise

*int* *fontWidth*

[in] Font width.

*int* *fontHeight*

[in] Font height.

*char\** *text*

[in]Text data.

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.12 ZPL\_Text

This function is to print text.

```
int ZPL_Text(  
    void* handle,  
    int xPos,  
    int yPos,  
    int fontNum,  
    int orientation,  
    int fontWidth,  
    int fontHeight,  
    char* text  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int fontNum*

[in] Font.

- 0 : FONT 0 - Scalable font
- 1 : FONT A - Bitmap font
- 2 : FONT B - Bitmap font
- 3 : FONT D - Bitmap font
- 4 : FONT E - Bitmap font
- 5 : FONT F - Bitmap font
- 6 : FONT G - Bitmap font
- 7 : FONT H - Bitmap font
- 8 : FONT GS - Bitmap font
- 9 : FONT P - Bitmap font
- 10 : FONT Q - Bitmap font
- 11 : FONT R - Bitmap font
- 12 : FONT S - Bitmap font
- 13 : FONT T - Bitmap font
- 14 : FONT U - Bitmap font
- 15 : FONT V - Bitmap font
- 16 : SIMSUN.TTF – Song font
- 17 : FONT Z - Vietnam font

*int orientation*

[in] Print direction.

- 0 : normal
- 90 : Rotate 90 degrees clockwise
- 180 : Rotate 180 degrees clockwise
- 270 : Rotate 270 degrees clockwise

*int fontWidth*

[in] Font width.

*int fontHeight*

[in] Font height.

**Note:** When FONT Z is selected, the minimum width and height are 12\*24, and can only be multiplied.

*char\* text*

[in]Text data.

**FONT A** -- ABCDxyz 12345

**FONT B** -- ABCDWXYZ 12345 UPPER CASE ONLY

**FONT D** -- ABCDwxyz 12345

**FONT E** -- **(OCR-B)ABCDwxyz 12345**

**FONT F** -- ABCDwxyz 12345

**FONT G** -- **AByz 12**

**FONT H** -- **(OCR-A) UPPER CASE ONLY**

**FONT O** -- **(Scaleable) ABCDwxyz 12345**

**FONT GS** -- © ® ™ ®

**FONT P** -- ABCDwxyz 12345

**FONT Q** -- ABCDwxyz 12345

**FONT R** -- ABCDwxyz 12345

**FONT S** -- ABCDwxyz 12345

**FONT T** -- ABCDwxyz 12345

**FONT U** -- ABCDwxyz 12345

**FONT V** -- **ABCDwxyz 12345**

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.13 ZPL\_BarCode39

This function is to print Barcode39 barcodes.

```
int ZPL_BarCode39(  
    void* handle,  
    int xPos,  
    int yPos,  
    int orientation,  
    int moduleWidth,  
    int codeHeight,  
    char line,  
    char lineAboveCode,  
    char digit,  
    char* text  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int orientation*

[in] Print direction.

0 : normal

90 : Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise

*int moduleWidth*

[in] Bar code width (range: 0-10,unit:dot).

*int codeHeight*

[in] Bar code height(range: 1-32000,unit:dot).

*char line*

[in] Comment line.

'N': not print

'Y': print

*char lineAboveCode*

[in] The comment line above the barcode.

'N': not print above the barcode

'Y': print above the barcode

*char digit*

[in] Check Digit.

'N': do not print check digit

'Y': print check digit

*char\* text*

[in] Text data.

#### **Return Value:**

<b>Error code</b>	<b>Value</b>	<b>Description</b>
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.14 ZPL\_Pdf417

This function is to print the Pdf417 code.

```
int ZPL_Pdf417(  
    void* handle,  
    int xPos,  
    int yPos,  
    int orientation,  
    int moduleWidth,  
    int codeHeight,  
    int securityLevel,  
    int column,  
    int rows,  
    char truncate,  
    char* text  
);
```

### Parameter:

*void\* handle*

[in,out]The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).



*int orientation*

[in] Print direction.

0 : normal

90 : Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise

*int moduleWidth*

[in] Bar code width (range: 0-10,unit:dot).

*int codeHeight*

[in] Bar code height(range: 1-32000,unit:dot).

*int securityLevel*

[in] Security level (range:1-8).

*int column*

[in] The number of columns to encode.

*int rows*

[in] The number of rows to encode.

*char truncate*

[in] Truncated layer indication and stop mode.

'N': not truncated

'Y': execution truncation

*char\* text*

[in] QR code data.

#### **Return value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.15 ZPL\_CodeEan8

This function is to print CodeEan8 barcodes.

```
int ZPL_CodeEan8(  
    void* handle,  
    int xPos,  
    int yPos,  
    int orientation,  
    int moduleWidth,  
    int codeHeight,  
    char line,  
    char lineAboveCode,  
    char* text  
);
```

### Parameter:

*void\* handle*

[in,out]The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int orientation*

[in] Print direction.

0 : normal

90 : Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise

*int moduleWidth*

[in] Bar code width (range: 0-10,unit:dot).

*int codeHeight*

[in] Bar code height(range: 1-32000,unit:dot).

*char line*

[in] Comment line.

'N': not print

'Y': print

*char lineAboveCode*

[in] The comment line above the barcode.

'N': not print above the barcode

'Y': print above the barcode

*char\* text*

[in] Text data.

#### **Return Value:**

<b>Error code</b>	<b>Value</b>	<b>Description</b>
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.16 ZPL\_UpceCode

This function is to print UPC-E barcodes.

```
int ZPL_UpceCode(  
    void* handle,  
    int xPos,  
    int yPos,  
    int orientation,  
    int moduleWidth,  
    int codeHeight,  
    char line,  
    char lineAboveCode,  
    char* text  
);
```

### Parameter:

*void\* handle*

[in,out]The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int orientation*

[in] Print direction.

0 : normal

90: Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise

*int moduleWidth*

[in] Bar code width (range: 0-10,unit:dot).

*int codeHeight*

[in] Bar code height(range: 1-32000,unit:dot).

*char line*

[in] Comment line.

'N': not print

'Y': print

*char lineAboveCode*

[in] The comment line above the barcode.

'N': not print above the barcode

'Y': print above the barcode

*char\* text*

[in] Text data.

#### **Return Value:**

<b>Error code</b>	<b>Value</b>	<b>Description</b>
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.17 ZPL\_BarCode93

This function is to print Barcode93 barcodes.

**int ZPL\_BarCode93(**

**void\*** *handle*,

**int** *xPos*,

**int** *yPos*,

**int** *orientation*,

**int** *moduleWidth*,

**int** *codeHeight*,

**char** *line*,

**char** *lineAboveCode*,

**char** *digit*,

**char\*** *text*

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int orientation*

[in] Print direction.

0 : normal

90 : Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise

*int moduleWidth*

[in] Bar code width (range: 0-10,unit:dot).

*int codeHeight*

[in] Bar code height(range: 1-32000,unit:dot).

*char line*

[in] Comment line.

'N': not print

'Y': print

*char lineAboveCode*

[in] The comment line above the barcode.

'N': not print above the barcode

'Y': print above the barcode

*char digit*

[in] Check Digit.

'N': do not print check digit

'Y': print check digit

*char\* text*

[in] Text data.

#### **Return Value:**

<b>Error code</b>	<b>Value</b>	<b>Description</b>
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.18 ZPL\_BarCode128

This function is to print Barcode128 barcodes.

```
int ZPL_BarCode128(  
    void* handle,  
    int xPos,  
    int yPos,  
    int orientation,  
    int moduleWidth,  
    int codeHeight,  
    char line,  
    char lineAboveCode,  
    char checkDigit,  
    char mode,  
    char* text  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).



*int orientation*

[in] Print direction.

0 : normal

90 : Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise

*int moduleWidth*

[in] Bar code width (range: 0-10,unit:dot).

*int codeHeight*

[in] Bar code height(range: 1-32000,unit:dot).

*char line*

[in] Comment line.

'N': not print

'Y': print

*char lineAboveCode*

[in] The comment line above the barcode.

'N': not print above the barcode

'Y': print above the barcode

*char checkDigit*

[in] UCC check Digit.

'N': do not print check digit

'Y': print check digit

*char mode*

[in] Mode.

'N': no choice mode

'U': UCC matching mode

'A': automatic mode

'D': UCC/EAN mode

*char\* text*

[in] Text data.

#### **Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.19 ZPL\_CodeEan13

This function is to print CodeEan13 barcodes.

```
int ZPL_CodeEan13(  
    void* handle,  
    int xPos,  
    int yPos,  
    int orientation,  
    int moduleWidth,  
    int codeHeight,  
    char line,  
    char lineAboveCode,  
    char* text  
);
```

### Parameter:

*void\* handle*

[in,out]The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int orientation*

[in] Print direction.

0 : normal

90 : Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise

*int moduleWidth*

[in] Bar code width (range: 0-10,unit:dot).

*int codeHeight*

[in] Bar code height(range: 1-32000,unit:dot).

*char line*

[in] Comment line.

'N': not print

'Y': print

*char lineAboveCode*

[in] The comment line above the barcode.

'N': not print above the barcode

'Y': print above the barcode

*char\* text*

[in] Text data.

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.20 ZPL\_MicroPdf417

This function is to print MicroPdf417 codes.

**int ZPL\_MicroPdf417(**

**void\*** *handle*,

**int** *xPos*,

**int** *yPos*,

**int** *orientation*,

**int** *moduleWidth*,

**int** *codeHeight*,

**int** *mode*,

**char\*** *text*

**);**

### **Parameter:**

*void\* handle*

[in,out]The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int orientation*

[in] Print direction.

0 : normal

90 : Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise

*int moduleWidth*

[in] Bar code width (range: 0-10,unit:dot).

*int codeHeight*

[in] Bar code height(range: 1-32000,unit:dot).

*int mode*

[in] Mode(range: 0-33).

Mode (M)	Number of Data Columns	Number of Data Rows	% of Cws for EC	Max Alpha Characters	Max Digits
0	1	11	64	6	8
1	1	14	50	12	17
2	1	17	41	18	26
3	1	20	40	22	32
4	1	24	33	30	44
5	1	28	29	38	55
6	2	8	50	14	20
7	2	11	41	24	35
8	2	14	32	36	52
9	2	17	29	46	67
10	2	20	28	56	82
11	2	23	28	64	93
12	2	26	29	72	105
13	3	6	67	10	14
14	3	8	58	18	26
15	3	10	53	26	38
16	3	12	50	34	49
17	3	15	47	46	67
18	3	20	43	66	96
19	3	26	41	90	132
20	3	32	40	114	167
21	3	38	39	138	202
22	3	44	38	162	237
23	4	6	50	22	32
24	4	8	44	34	49
25	4	10	40	46	67
26	4	12	38	58	85
27	4	15	35	76	111
28	4	20	33	106	155
29	4	26	31	142	208
30	4	32	30	178	261
31	4	38	29	214	313
32	4	44	28	250	366
33	4	4	50	14	20

*char\* text*

[in] Text data.

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.21 ZPL\_QRCode

This function is to print a QR code.

```
int ZPL_QRCode(  
    void* handle,  
    int xPos,  
    int yPos,  
    int orientation,  
    int model,  
    int dpi,  
    char eccLevel,  
    int maskMode,  
    char* text  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int orientation*

[in] Print direction.

0 : normal

90 : Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise

*int model*

[in] Set the QR code version (1: original version, 2: enhanced version).

*int dpi*

[in] Magnification factor (range: 1-10).

*char eccLevel*

[in] Error correction level.

H: Ultra high reliability

Q: High reliability

M: standard level

L: high density level

*int maskMode*

[in] Mask mode (range: 0-7).

*char\* text*

[in] QR code data.

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.22 ZPL\_UpcExtensions

This function is to print UPC extended barcodes.

```
int ZPL_UpcExtensions(  
    void* handle,  
    int xPos,  
    int yPos,  
    int orientation,  
    int moduleWidth,  
    int codeHeight,  
    char line,  
    char lineAboveCode,  
    char* text  
);
```

### Parameter:

*void\* handle*

[in,out]The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int orientation*

[in] Print direction.

0 : normal

90 : Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise



*int moduleWidth*

[in] Bar code width (range: 0-10,unit:dot).

*int codeHeight*

[in] Bar code height(range: 1-32000,unit:dot).

*char line*

[in] Comment line.

'N': not print

'Y': print

*char lineAboveCode*

[in] The comment line above the barcode.

'N': not print above the barcode

'Y': print above the barcode

*char\* text*

[in] Text data.

#### **Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.23 ZPL\_UpcaBarcode

This function is to print UPC-A barcodes.

**int ZPL\_UpcaBarcode(**

**void\*** *handle*,

**int** *xPos*,

**int** *yPos*,

**int** *orientation*,

**int** *moduleWidth*,

**int** *codeHeight*,

**char** *line*,

**char** *lineAboveCode*,

**char** *digit*,

**char\*** *text*

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int orientation*

[in] Print direction.

0 : normal

90 : Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise

*int moduleWidth*

[in] Bar code width (range: 0-10,unit:dot).

*int codeHeight*

[in] Bar code height(range: 1-32000,unit:dot).

*char line*

[in] Comment line.

'N': not print

'Y': print

*char lineAboveCode*

[in] The comment line above the barcode.

'N': not print above the barcode

'Y': print above the barcode

*char digit*

[in] Check Digit.

'N': do not print check digit

'Y': print check digit

*char\* text*

[in] Text data.

#### **Return Value:**

<b>Error code</b>	<b>Value</b>	<b>Description</b>
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.24 ZPL\_SetChangeFontEncoding

This function is to select an international character set.

```
int ZPL_SetChangeFontEncoding(  
  
    void* handle,  
  
    int encodeType  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int encodeType*

[in] Character set type (range: 0-31, 33-36).

- 0 : single byte encoding - US 1 character set
- 1 : Single-byte encoding - US 2 character set
- 2 : Single Byte Encoding - British Character Set
- 3 : Single Byte Encoding - Dutch Character Set
- 4 : Single-byte encoding - Danish/Norwegian character set
- 5 : Single-byte encoding - Swedish/Finnish character set
- 6 : Single byte encoding - German character set
- 7 : Single-byte encoding - French 1 character set
- 8 : Single-byte encoding - French 2 character set
- 9 : Single-byte encoding - Italian character set
- 10 : Single Byte Encoding - Spanish Character Set
- 11 : Single Byte Encoding - Miscellaneous Character Set
- 12 : Single-byte encoding - Japanese character set
- 13 : Code Page 850
- 14 : Double Byte Asian Code
- 15 : Shift-JIS
- 16 : EUC-JP and EUC-CN
- 17 : Not recommended - UCS-2 Big Endian
- 18-23 : Reserved
- 24 : Single Byte Asian Code
- 25 : Reserved
- 26 : Multibyte Asian Code

27 : Code Page 1252  
28 : Unicode (UTF-8 encoding) - Unicode character set  
29 : Unicode (UTF-16 Big-Endian encoding) - Unicode character set  
30 : Unicode (UTF-16 Little-Endian encoding) - Unicode character set  
31 : Code Page 1250  
33 : Code page 1251  
34 : Code page 1253  
35 : Code page 1254  
36 : Code page 1255  
39 : Vietnam Character Set

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.25 ZPL\_SetChangeCaret

This function is to change the format command prefix.

```
int ZPL_SetChangeCaret(
```

```
    void* handle,
```

```
    char charactor
```

```
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char charactor*

[in] Format command prefix.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.26 ZPL\_SetChangeDelimiter

This function is to change the separator.

```
int ZPL_SetChangeDelimiter(  
  
    void* handle,  
  
    char charactor  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char charactor*

[in] Separator.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.27 ZPL\_SetChangeTilde

This function is to change the control command prefix.

```
int ZPL_SetChangeTilde(  
  
    void* handle,  
  
    char charactor  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char charactor*

[in] Control command prefix.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout



## 4.28 ZPL\_GraphicBox

This function is to draw a graphic box.

**int ZPL\_GraphicBox(**

**void\*** *handle*,

**int** *xPos*,

**int** *yPos*,

**int** *width*,

**int** *height*,

**int** *thickness*,

**int** *rounding*,

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int width*

[in] The width of the box (range: 1-32000, unit: dot).

*int height*

[in] The height of the box (range: 1-32000, unit: dot).

*int thickness*

[in] Boundary thickness (range: 1-32000, unit: dot).

*int rounding*

[in] Degree of rotation (range: 0-8).

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.29 ZPL\_GraphicCircle

This function is to draw a graphic circle.

**int ZPL\_GraphicCircle(**

**void\*** *handle*,

**int** *xPos*,

**int** *yPos*,

**int** *diameter*,

**int** *thickness*,

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int diameter*

[in] Round diameter(range:3-4095,unit:dot).

*int thickness*

[in] Boundary thickness(range:1-4095,unit:dot).

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.30 ZPL\_GraphicDiagonalLine

This function is to draw diagonals.

```
int ZPL_GraphicDiagonalLine(  
  
    void* handle,  
  
    int xPos,  
  
    int yPos,  
  
    int orientation,  
  
    int width,  
  
    int height,  
  
    int thickness  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int orientation*

[in] The direction of the diagonal.

0x52(R or /) : right slanted diagonal

0x4c (L or \) : left slanted diagonal

*int width*

[in] The width of the box (range: 1-32000, unit: dot).

*int height*

[in] The height of the box (range: 1-32000, unit: dot).

*int thickness*

[in] Boundary thickness (range: 1-32000, unit: dot).

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.31 ZPL\_GraphicEllipse

This function is to draw a graphical ellipse.

```
int ZPL_GraphicEllipse(  
    void* handle,  
    int xPos,  
    int yPos,  
    int width,  
    int height,  
    int thickness  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int width*

[in] Ellipse width (range: 3-4095, unit: dot).

*int height*

[in] Ellipse height (range: 3-4095, unit: dot).

*int thickness*

[in] Boundary thickness (range: 2-4095, unit: dot).

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.32 ZPL\_PrintImage

This function is to print image.

```
int ZPL_PrintImage(  
  
    void* handle,  
  
    int xPos,  
  
    int yPos,  
  
    char* imgName  
  
);
```

### parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*char\* imgName*

[in] The path to the image.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout



## 4.33 ZPL\_GraphicSymbol

This function is to generate registered trademarks, copyright symbols and other symbols.

**int ZPL\_GraphicSymbol(**

**void\*** *handle*,

**int** *xPos*,

**int** *yPos*,

**int** *orientation*,

**int** *width*,

**int** *height*,

**char\*** *type*

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int orientation*

[in] Print direction.

0 : normal

90 : Rotate 90 degrees clockwise

180: Rotate 180 degrees clockwise

270: Rotate 270 degrees clockwise

*int width*

[in] Symbol width.

*int height*

[in] Symbol height.

*char\* type*

[in] Data string.

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.34 ZPL\_SetDiagnosticsMode

This function is to start the diagnostic mode.

```
int ZPL_SetDiagnosticsMode(  
  
    void* handle,  
  
    int isEnabled  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int isEnabled*

[in] Whether to enable the diagnostic mode.

1 : Turn on diagnostic mode

0 : Cancel diagnostic mode

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.35 ZPL\_SetLabelHome

This function is to set the label home position.

```
int ZPL_SetLabelHome(
```

```
    void* handle
```

```
    int xPos,
```

```
    int yPos
```

```
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.36 ZPL\_SetLabelLength

This function is to set the label length.

```
int ZPL_SetLabelLength(
```

```
    void* handle,
```

```
    int length
```

```
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int length*

[in] Label length (range: 1-32000, unit: dot).

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.37 ZPL\_SetLabelShift

This function is to move the contents of the label to the left.

**int ZPL\_SetLabelShift(**

**void\* *handle*,**

**int *shift***

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int shift*

[in] The value to move to the left (range: -9999–9999, unit: dot).

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.38 ZPL\_SetLabelTop

This function is to move the position of the label up or down a short distance relative to the top edge of the label.

**int ZPL\_SetLabelTop(**

**void\* *handle*,**

**int *top***

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int top*

[in] Maximum degree (range: -120–120, unit: dot).

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.39 ZPL\_SetPrintMode

This function is to set the action the printer performs after printing a label or label group.

**int ZPL\_SetPrintMode(**

**void\*** *handle*,

**char** *mode*,

**char** *prePeelSelect*

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char mode*

[in] Operating mode.

'T': tear open

'P': stripping (depending on the printer model)

'R': rewind (depending on the printer model)

'A': applicator (depending on printer model)

'C': cutter (depending on printer model)

'D': cutter delay

'F': RFID

'L': reserved

'U': reserved

'K': Kiosk

*char prePeelSelect*

[in] select.

'N': not execute

'Y': execute

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout



## 4.40 ZPL\_SetMediaType

This function is to select the type of media used in the printer.

**int ZPL\_SetMediaType(**

**void\* *handle*,**

**char *type***

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char type*

[in] Media type.

‘T’ : thermal transfer media

‘D’ : direct thermal media

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.41 ZPL\_SetPrintingMirrorImage

This function is to print the entire printable area of the label as a mirror image.

```
int ZPL_SetPrintingMirrorImage(
```

```
    void* handle,
```

```
    char enable
```

```
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char enable*

[in] Whether to open.

‘N’: not open

‘Y’: open

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.42 ZPL\_SetPrintOrientation

This function is to flip the label format 180 degrees.

**int ZPL\_SetPrintOrientation(**

**void\* *handle*,**

**int *orientation***

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int orientation*

[in] Whether to flip.

0: don't flip

180: perform a flip

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.43 ZPL\_SetPrintRate

This function is to set the print speed.

```
int ZPL_SetPrintRate(  
  
    void* handle,  
  
    int printSpeed,  
  
    int slewSpeed,  
  
    int backfeedSpeed  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int printSpeed*

[in] Print speed. (unit: inches/sec)

*int slewSpeed*

[in] Swing speed. (unit: inches/sec)

*int backfeedSpeed*

[in] Feedback speed. (unit: inches/sec)

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.44 ZPL\_SetPrintWidth

This function is to set print width.

**int ZPL\_SetPrintWidth(**

**void\* *handle*,**

**int *width***

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int width*

[in] Set the print width (range: 2-944, unit: dot).

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.45 ZPL\_SetSerialCommunications

This function is to change the serial communication parameters.

**int ZPL\_SetSerialCommunications(**

**void\*** *handle*,

**int** *baudRate*,

**int** *wordLength*,

**char** *parity*,

**int** *stopBits*,

**char** *protocolModo*,

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int baudRate*

[in] Bandwidth frequency. The scope is as follows:

110	300	600	1200	2400
4800	9600	14400	19200	28800
38400	57600	115200		

*int wordLength*

[in] Word length: 7-8, unit: data bits.

*char parity*

[in] as follows:

'N': means: none.

'E': means: even.

'O': means: odd.

*int stopBits*

[in] Range: 1-2.

*char protocolModo*

[in] as follows:

'X': indicates: XON/XOFF.

'D': indicates: DTR/DSR.

'R': indicates: RTS.

'M': indicates: DTR/DSR XON/XOFF r.

remark: 1、XON/XOFF (transmitter on/transmitter off)

2、DTR (Data Terminal Ready)

3、DSR (Data Set Ready)

4、RTS (Request To Send)

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.46 ZPL\_SetPrintDarkness

This function is to set print darkness.

```
int ZPL_SetPrintDarkness (  
  
    void* handle,  
  
    int darkness  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int darkness*

[in] Print darkness(Range: 0-30, unit: dot).

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout



## 4.47 ZPL\_SetTearOffAdjustPosition

This function is to set the position where the label is torn away.

**int ZPL\_SetTearOffAdjustPosition (**

**void\*** *handle*,

**int** *position*

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int position*

[in] Peel off position (range: -120~+120).

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.48 ZPL\_PrintConfigurationLabel

This function is to generate a printer configuration label.

```
int ZPL_PrintConfigurationLabel(  
  
    void* handle  
  
);
```

### Parameter:

*void\* handle*  
[in,out] The created target printer object.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.49 ZPL\_GetPrinterIpAddress

This function is to get the printer IP address.

**int ZPL\_GetPrinterIpAddress(**

**void\* *handle***

**char\* *ipAddress***

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char\* ipAddress*

[in] Printer's IP address.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.50 ZPL\_GetPrinterStatus

This function is to get the status of the printer.

**int ZPL\_GetPrinterStatus (**

**void\* *handle*,**

**int\* *status***

**);**

**Parameter:**

*void\* handle*

[in,out] The created target printer object.

*int\* status*

[in] The status of the printer.

E.g: 00 00 12 34 Convert to binary 0000 0000 0000 0000 0001 0010 0011 0100(bit32<-bit0)

The corresponding bit is 1 as follows:

Status	Value
Normal	0
Standby	1
Label End	2
TOF Error	3
Label End	4
Ribbon End	5
Label Seizing	6
Label Jumpping	7
Label Calibrating	8
Cuter Error	9
Form Error	10
Memory Write Error	11
illegal Command	12
Lid Not In Place	13
Ribbon Almost End	14

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.51 ZPL\_GetLabelLength

This function is to get the length of the label.( not available on HT130/300)

**int ZPL\_GetLabelLength (**

**void\* *handle*,**

**char\* *length***

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char\* length*

[in] The length of the label.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.52 ZPL\_GetLabelWidth

This function is to get the width of the label. ( not available on HT130/300)

**int ZPL\_GetLabelWidth(**

**void\* *handle*,**

**char\* *width***

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char\* width*

[in] The width of the label.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.53 ZPL\_GetPrinterSeriesNumber

This function is to get the printer serial number.

```
int ZPL_GetPrinterSeriesNumber(
```

```
    void* handle,
```

```
    char* sn
```

```
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char\* sn*

[in] Printer serial number.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout



## 4.54 ZPL\_GetPrinterMacAddress

This function is to get the printer's MAC address.

```
int ZPL_GetPrinterMacAddress(
```

```
    void* handle,
```

```
    char* macAddress
```

```
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char\* macAddress*

[in] The MAC address of the printer.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.55 ZPL\_GetPrinterName

This function is to get the printer's name.

```
int ZPL_GetPrinterName(
```

```
    void* handle,
```

```
    char* name
```

```
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char\* name*

[in] The name of the printer.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.56 ZPL\_GetPrinterFirmwareVersion

This function is to get the firmware version number of the printer.

```
int ZPL_GetPrinterFirmwareVersion(
```

```
    void* handle,
```

```
    char* version
```

```
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char\* version*

[in] The firmware version number of the printer.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.57 ZPL\_GetPrinterDpi

This function is to get the resolution of the printer.

```
int ZPL_GetPrinterDpi(
```

```
    void* handle,
```

```
    char* dpi
```

```
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char\* dpi*

[in] The resolution of the printer.

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.58 ZPL\_LearnLabel

This feature is used for automatic label learning.

```
int ZPL_LearnLabel(
```

```
    void* handle,
```

```
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

(The interface needs to be called before ZPL\_StartFormat)

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.59 ZPL\_SetReprintAfterError

This function is to reprint the labels that failed to print due to an error (error conditions include Ribbon Out, Media Out, Head Open).

**int ZPL\_SetReprintAfterError(**

**void\* *handle*,**

**char\* *pEnable***

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*Char\* pEnable*

[in] Whether to enable reprint.

“on”: turn on reprint switch

“off”: close reprint switch

(The interface needs to be called before ZPL\_StartFormat)

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.60 ZPL\_SetNetworkSetting

This function is to change the network settings on the printer.

**int ZPL\_SetNetworkSetting(**

**void\* *handle*,**

**char\* *network***

**);**

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*char\* network*

[in] **Format** "a,b,c,d,e,f,g,h,i,j"

a position (the device that is being modified):

1 express: external wired;

2 express: internal wired;

3 express: wireless;

b position (IP resolution):

A express: All;

B express: BOOTP;

C express: DHCP and BOOTP;

D express: DHCP;

G express: Gleaning only (Not recommended when the Wireless Print Server

or Wireless Plus Print Server is installed.);

R express: RARP;

P express: Permanent;

c position (IP address) : format: xxx.xxx.xxx.xxx

d position (subnet mask) : format: xxx.xxx.xxx.xxx

e position (default gateway) : format: xxx.xxx.xxx.xxx

f position (WINS server address) : format: xxx.xxx.xxx.xxx

g position (connection timeout checking) : Whether timeout detection: Y=yes, N=no

h position (timeout value) : range: 0-9999。

i position (ARP broadcast interval) :range: 0-30。

j position (ARP broadcast interval) :range: 1-65535。

Parameter setting example: "1, A, 192.168.1.1, 255.255.255.0, 192.168.1.1, 192.168.1.1, Y, 300, 0, 9100"

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout



## 4.61 ZPL\_SetMediaTracking

This function is to specify the media type being used and the black mark offset.

**int ZPL\_SetMediaTracking(**

**void\*** *handle*,

**char** *mediaType*,

**int** *offset*

**);**

### Parameter:

**void\*** *handle*

[in,out] The created target printer object.

**char** *mediaType*

[in] Media Type.

‘N’: continuous media(continuous paper)

‘Y’: non-continuous media web sensing(label paper)

‘W’: non-continuous media web sensing(label paper)

‘M’: non-continuous media mark sensing(black mark paper)

‘A’: auto-detects the type of media during calibration

‘V’: continuous media, variable length(Same as continuum, but if the portion of the printed label exceeds the defined label length, the label size will automatically expand to include them)

**int** *offset*

[in] Black mark offset (unused, set to 0) .

### Return Value:

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.62 ZPL\_SetUserFontName

This function is to Set user-defined fonts,use for print text

```
int ZPL_SetPrintDefaultGateway (  
  
    void* handle  
  
    const TCHAR* text  
  
);
```

参数:

*void\* handle*  
[in,out] The created target printer object.  
*const TCHAR\* text*  
[in] Font name

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.63 ZPL\_SetVietMode

This function is to Set Vietnamese mode

```
int ZPL_SetVietMode(  
  
    void* handle  
  
    int vietmode  
  
);
```

参数:

*void\* handle*

[in,out] The created target printer object.

*int vietmode*

[in] mode

1: ASCII

2: UTF-8

(The interface needs to be called before ZPL\_StartFormat)

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.64 ZPL\_SetVietFontEncoding

This function is to set Vietnamese character

```
int ZPL_SetVietFontEncoding(
```

```
    void* handle
```

```
);
```

参数:

*void\* handle*

[in,out] The created target printer object.

(The interface needs to be called before ZPL\_StartFormat)

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout

## 4.65 ZPL\_Text\_Block

This function is to print text block.

```
int ZPL_Text_Block(  
  
    void* handle,  
  
    int xPos,  
  
    int yPos,  
  
    int fontNum,  
  
    int orientation,  
  
    int fontWidth,  
  
    int fontHeight,  
  
    int textBlockWidth,  
  
    int textBlockHeight,  
  
    char* text  
  
);
```

### Parameter:

*void\* handle*

[in,out] The created target printer object.

*int xPos*

[in] Horizontal starting position (range: 0-32000,unit:dot).

*int yPos*

[in] Vertical starting position (range: 0-32000,unit:dot).

*int fontNum*

[in] Font.

- 0 : FONT 0 - Scalable font
- 1 : FONT A - Bitmap font
- 2 : FONT B - Bitmap font
- 3 : FONT D - Bitmap font
- 4 : FONT E - Bitmap font
- 5 : FONT F - Bitmap font
- 6 : FONT G - Bitmap font
- 7 : FONT H - Bitmap font
- 8 : FONT GS - Bitmap font
- 9 : FONT P - Bitmap font
- 10 : FONT Q - Bitmap font
- 11 : FONT R - Bitmap font
- 12 : FONT S - Bitmap font
- 13 : FONT T - Bitmap font
- 14 : FONT U - Bitmap font
- 15 : FONT V - Bitmap font

FONT A -- ABCDwxyz 12345

FONT B -- ABCDHXYZ 12345 UPPER CASE ONLY

FONT D -- ABCDwxyz 12345

FONT E -- (OCR-B) ABCDwxyz 12345

FONT F -- ABCDwxyz 12345

FONT G -- **AByz 12**

FONT H -- (OCR-A) UPPER CASE ONLY

FONT O -- (Scaleable) ABCDwxyz 12345

FONT GS -- © ® ™ ®

FONT P -- ABCDwxyz 12345

FONT Q -- ABCDwxyz 12345

FONT R -- ABCDwxyz 12345

FONT S -- ABCDwxyz 12345

FONT T -- ABCDwxyz 12345

FONT U -- **ABCDwxyz 12345**

FONT V -- **ABCDwxyz 12345**

*int orientation*

[in] Print direction.

- 0 : normal
- 90 : Rotate 90 degrees clockwise
- 180 : Rotate 180 degrees clockwise
- 270 : Rotate 270 degrees clockwise

*int fontWidth*

[in] Font width.

*int fontHeight*

[in] Font height.

*int textBlockWidth*

[in] Text block width

*int textBlockHeight*

[in] Text block height

*char\* text*

[in]Text data.

Note: The data does not support Chinese at this time

**Return Value:**

Error code	Value	Description
E_SUCCESS	0	Normal
E_INVALID_PARAMETER	-1	Invalid parameter
E_NOT_ENOUGH_BUFFER	-2	No enough memory
E_INVALID_MODEL_TYPE	-3	This model does not support this feature.
E_BAD_HANDLE	-6	Invalid handle
E_IO_PORT_NOT_OPEN	-309	Communication port not open
E_IO_WRITE_FAILED	-321	Write failed
E_IO_WRITE_TIMEOUT	-322	Write timeout